

TRANSFORMER BDV OIL TEST SET

Quality | Accuracy | Reliability







Oil test set is an equipment designed to test the dielectric strength of insulating oils as per relevant specification viz. IS 6972 it is a useful equipment for transformer/switchgear manufacturing units. Oil filtering agencies, repair shop and electrical maintenance departments.

SPECIFICATION:

Input: 230AC, 1Phase, 50Hz.

Output : 0-60/80/100 KV, center tap earthed

Capacity: 1KVA

Indication : Mains 'ON', HT 'ON' & 'OFF' Lamps Metering : 96 sq.mm. Analog / Digital Voltmeter to

monitor output voltage.

Protection: Electronic, fast action over-current tripping

device sensing HT Current directly

Motorisation: The unit will be supplied with the rate of

rise of voltage @ 2KV/second and in case of motorization failure, the unit can

be operated manually.

SAFETY FEATURES:

- 1) Zero Inter-Locking arrangement
- 2) A transparent hood (cover) on test cup with a door interlocking micro switch
- 3) Resin encapsulated HT transformer
- 4) The test cell is made from transparent high impact Acrylic sheet which enables the operator to observe the flash over of the oil under test

CONSTRUCTION:

It is in Portable Air Cooled Sheet Metal Casting with Powder Coating Consists of control cubical and H. T. Transformer

OPTIONAL:

1) Magnetic Stirrer Facility is also available on request 2) Dig

2) Digital Timer can be provided.

ACCESSORIES:

1) 'GO' & 'NO GO' Gauge 2) Test Cell 3) Instruction Manual

OUR RANGE OF PRODUCTS:

- □ Digital Panel Meter
- Secondary Current Injection Kit
- Automatic Power Factor Control Relay
- → Primary Current Injection Kit
- A.C. / D.C. High Voltage Testing Kits.
- □ Cont. Variable Voltage Auto Transformers.
- ☐ Transformer Turns Ratio Testers.
- □ Transformer Winding Resistance Tester
- □ Digital Micro Ohms Meters.
- Automatic Power Factor Control Relays.

- ☐ Automatic Voltage Regulating Relays.
- □ Digital Tap Position Indicators.
- □ Digital Oil Temperature Indicators
- □ Digital Winding Temperature Indicators.
- ☐ Digital Set Point Relays for Current/Voltage.
- ☐ Digital Multifunctional Power Energy Meters
- ☐ Auto Reclosing Relays.
- ☐ Insulation Testers.
- □ Earth Testers.

Product Specifications are subject to change without notice

Manufactured By:

NEUTRONICS MANUFACTURING CO.

12-A, JOY COMPOUND, MAROL MAROSHI ROAD,

ANDHERI (E), MUMBAI - 400059. TEL: 022-2925 0745 / 2920 1296. MOB: 98194 50890 / 98190 70556.

Email: sales@neutronics.co.in / bhavin_nmc@yahoo.com / mehul@neutronics.co.in

Marketed By: